CHDC-D400/500SL/SLA Series DC contactor



FEATURES

- 400A/500A Contact switching capability
- Bistable, initial normally open and normally closed optional, auxiliary contacts optional.
- Meet cULus,CCC Requirements (UL60947-4-1 , IEC60947-4-1 , GB/T 14048.4)
- RoHS compliance
- REACH SvHC compliance







APPLICATION

 $\label{thm:construction} Telecommunication equipment, construction machinery, battery car, \\ Electric forklift, automobile, Train, Ship, \\$

Uninterruptible power supply and other electronic control systems.

COILDATA @23℃

CHDC-D400SL/SLA								
Nominal Voltage (VDC)	Rated Power (W)	Rated Current (A)	coil resistance $(\Omega)\pm10\%$	Operate Voltage (VDC MAX.)	Release Voltage (VDC Min.)			
12	Approx. 21 (Standard)	1.75	6.9	9.0	9.0			
24		0.88	27.4	18.0	18.0			
48		0.44	110.0	36.0	36.0			
60		0.35	171.4	45.0	45.0			
12	Approx. 24 (High Power)	2.00	6.0	9.0	9.0			
24		1.00	24.0	18.0	18.0			
48		0.50	96.0	36.0	36.0			
60		0.40	150.0	45.0	45.0			

CHDC-D500SL/SLA								
Nominal Voltage (VDC)	Rated Power (W)	Rated Current (A)	coil resistance (Ω)±10%	Operate Voltage (VDC MAX.)	Release Voltage (VDC Min.)			
12	Approx. 24	2.00	6.0	9.0	9.0			
24		1.00	24.0	18.0	18.0			
48		0.50	96.0	36.0	36.0			
60		0.40	150.0	45.0	45.0			


CONTACT DATA

TYPE	CHDC-D400SL/SLA	CHDC-D500SL/SLA		
Contact arrangement	1A Bridge Form A or Bridge FormB (Initial)			
Contact material	Ag Alloy			
Initial contact resistance	0.5mΩ Max. (6VDC,20A)			
Rated insulation voltage	100VDC			
Max. switching voltage	80VDC			
Max. switching current (Resistive Load))	400A	500A		
Max. switching power	32,000W	40,000W		
Mechanicalendurance (No Load)	100,000 ops Min.(No Load)			
Electrical endurance (Resistive Load)	6,000 ops Min(Resistive Load)			
Minimum load (reference value)	100mA@ 48VDC			
Auxiliary switch Max. switching voltage	60VDC (Suitable for SLA series)			
Auxiliary switch Max. switching current (Resistive Load)	2A (Suitable for SLA series)			


CHARACTERISTICS

2 MΩ Min. (at 500 VDC)		
1,000 VAC, 50/60 Hz(1 Min)		
1,000 VAC, 50/60 Hz(1 Min)		
25,000V(1.2/50μs)		
25,000V(1.2/50μs)		
10 ~ 55 Hz.,Acceleration≤2G		
10 ~ 55 Hz.,Acceleration≤5G		
3G Min.		
50G Min.		
Operating: -40~+70°C (without icing or condensation)		
Screw installation (M10)		
478g		

The CHDC-D400SL/SLA series ORDERING INFORMATION





The CHDC-D500SL/SLA series ORDERING INFORMATION



OUTLINE DIMENSION

WIRING DIAGRAMS(BOTTOM VIEWS)






Contact Non-polarity




Coil Plus Positive Pulse, Contact Closed Coil Plus Negative Pulse, Contact Open

OUTLINE DIMENSION

WIRING DIAGRAMS(BOTTOM VIEWS)









Coil Plus Positive Pulse, Contact Closed Coil Plus Negative Pulse, Contact Open

Remark:


The reference tolerance in outline dimension: : outline dimension ≤ 1 mm, reference tolerance is ± 0.2 mm; outline dimension > 1mm and ≤ 5 mm, reference tolerance is ± 0.3 mm outline dimension > 5mm, reference tolerance is ± 0.5 mm.


CHDR-D400SL/SLA Series Reference Data





CHDR-D500SL/SLA Series Reference Data





PACKING





10 pcs inside a box 10 pcs inside a carton

Matters needing attention

- 1. When installing contactor, the tightening torque of main circuit connection screw and nut is 8 \sim 13N.m, and the tightening torque of control circuit connection screw and nut is 1 \sim 1.5N.m.
- 2. The starting coil power must be no less than the relay coil power. Otherwise, the relay can not operate normally.
- 3. The product is non-waterproof. Avoid use in the environment where relay case or terminals may contact water, solvent, or oil.
- 4. The coil cannot be energized for a long time. The allowable pulse width is $0.2 \sim 1 \, \text{sec.}$.

Disclaimer

The specification is for reference only, if you need more detail information, please contact Churod. We could not evaluate all the performance and all parameters for every possible application.

And the user should be in a right position to choose the suitable product for their own application. If there is any new need, please contact Churod for the technical service.